



作者 Author：車東穎                      版次 Version：3  
INCOMING INSPECTION STANDARD 生效日 Effective Date：

INCOMING INSPECTION STANDARD FOR A201SN02 TFT-LCD MODULES

---

## **AU OPTRONICS CORPORATION**

### **Specification for Approval**

#### **INCOMING INSPECTION STANDARD FOR A201SN02 TFT-LCD MODULES**

**(A- Grade)**

The content of this technical information  
is subject to change without notice.  
Please contact AU or its agent for  
further information.

**1. Scope:**

The incoming inspection standards shall be applied to TFT-LCD Modules (hereinafter called "Modules") that supplied by AU Optronics Corporation (hereinafter called "seller").

**2. Incoming inspection right:**

The buyer (customer) shall inspect the modules within twenty calendar days since the delivery date (the "inspection period" ) at its own cost. The results of the inspection (acceptance or rejection) shall be recorded in writing, and a copy of this writing will be promptly sent to the seller.

The buyer may, under commercially reasonable rejection procedures, reject an entire lot in the delivery involved. Within the inspection period, if the samples of modules within a lot show a number of unacceptable defects in accordance with this incoming inspection standards, the buyer must notify the seller in writing of any such rejection promptly, and not later than within three business days of the end of the inspection period.

Should the buyer fail to notify the seller within the inspection period, the buyer's right to reject the modules shall be lapsed and the modules shall be deemed to have been accepted by the buyer.

**3. Inspection sampling method:**

Unless agreed in writing, the method of incoming inspection shall be based on MIL-STD-105E.

3-1 Sampling type: Normal inspection, single sampling.

3-2 Sampling level: Level II.

3-3 Acceptable quality level (AQL):

Major defect: AQL=0.65%.

Minor defect: AQL=1.0%.

**4. Inspection instruments:**

4-1 Pattern generator: model LD-2000 or equivalent.

4-2 Video board: AU video board or equivalent. The output of the signal should comply with the specifications provided by AU.



## 7. Inspection Criteria:

### ■ Electrical Inspection

#### 7.1 Dot Defect

A. Every dot herein means a Sub-Pixel (each Red, Green or Blue color).

B. Bright Dot defect is defined as that the defective area of the dot is larger than 50% of the dot area and should be visible under 2% ND filter.

##### 7.1-1 Bright Dot

Bright Dot is defined as Dot (sub-pixel), which appears bright on the screen when the LCD module displayed at dark pattern.

Inspection Item	Criteria
R.G or B 1 dot	Max 3 allowed
Adjacent 2 dots	0
Minimum distance between bright dots	$\geq$ 15 mm

A partial bright dot damaged less than half size of sub-pixel is not counted as a bright dot defect and should be specified below.

Item	Criteria
5% Not-visible	Ignored
5% Visible 2% Not-visible	Max. 7 allowed
2% Visible	Max. 3 allowed

##### 7.1-2 Dark Dot

Dark Dot is defined as Dot (sub-pixel), which appears dark on the screen when the LCD Module displays at bright pattern.

Inspection Item	Criteria
R.G or B 1 dot	Max. 5 allowed
Adjacent 2 dots (horizontal and vertical)	2 pairs
Minimum distance between dark dots	$\geq$ 5 mm

##### 7.1-3

Total amount of Dot Defects	Max 7
-----------------------------	-------

Minimum distance between bright and dark dots  $\geq 10$  mm


■ Appearance Inspection

7.2 Polarizer Defects

- A. Extraneous substances that can be wiped out such as Finger Prints, particles are not considered defects.
- B. Defects on the Black Matrix (outside the Active Area) are not considered defects.


Inspection Items	Criteria
Linear Scratch	$0.1 \leq W \leq 0.15, L \leq 20, N \leq 6$
Bubble/Dent	$0.15 < D \leq 0.5, N \leq 6$

Where, W (mm): Width  
 L (mm): Length  
 D (mm): Average diameter



$D = (a+b)/2$

Note) Linear:  $a > 2b$ , Circular :  $a \leq 2b$




L = Longest point

7.3 Foreign Material


Inspection Items	Criteria
Linear	$0.1 < W \leq 0.15, L \leq 10, N \leq 6$
Circular	$0.15 < D \leq 0.5, N \leq 6$

Where, W (mm): Width  
 L (mm): Length  
 D (mm): Average diameter



$D = (a+b)/2$

Note) Linear:  $a > 2b$ , Circular :  $a \leq 2b$



L = Longest point

7.4 Bezel Appearance

Scratches, minor bents, stains, particles on the Bezel frame are not considered defects.

7.5 Mura

All other kinds of Mura should be invisible while 2% ND filter apply

## 8. Inspection judgment:

8.1 If the number of defects is more than the applicable acceptance level, the lot shall be rejected and the buyer should inform the seller of the result of incoming inspection in writing.

8.2 Issues which is not defined in this criteria shall be discussed by both parties, Customer and Supplier, for better solutions.

## 9. Precaution:

Please pay attention to the following items when you use the LCD Module.

9.1 Do not twist or bend the module and also avoid any inappropriate external force on display surface during assembly.

9.2 Adopt good ventilation measures. Be sure to use the module within the specified temperature range.

9.3 Avoid dust or oil mist during assembly.

9.4 Follow the correct power sequence while operating. Do not apply the invalid signal otherwise it will cause unexpected shutdown that damages the module.

9.5 The response time & brightness might vary at different temperature.

9.6 Avoid displaying at certain pattern (e.g. the white pattern) for a long time otherwise it might cause image sticking.

9.7 Be sure to turn off the power while connecting or disconnecting the circuit.

9.8 Display surface Polarizer scratches easily, please avoid dirt or stains on it and handle with care.

9.9 A dewdrop may cause malfunction or worse situation. Wipe off any before using the LCD module.

9.10 Sudden temperature change might cause condensation of materials and possible polarizer damage.

9.11 High temperature and high humidity might undermine the performance. Do not expose the module to the direct sunlight and so on.

9.12 Avoid any acetic acid or chlorine compounds, which are harmful to the LCD module.

9.13 Static electricity might damage the LCD module. Avoid direct touch of the module without any grounded device connected.

9.14 Do not disassemble and reassemble the module by yourself.

9.15 Do not touch the rear of the LCD module directly to avoid possible electric shock by the high voltage of backlight. Make sure the power is off before proceeding.

9.16 Avoid any strong vibration or shock, which might cause a broken LCD module.

9.17 Store the modules in cool and dry environment with regular packing.



作者 Author：車東穎                      版次 Version：3  
INCOMING INSPECTION STANDARD 生效日 Effective Date：

INCOMING INSPECTION STANDARD FOR A201SN02 TFT-LCD MODULES

---

9.18 Be careful of possible injury caused by a broken module. Also avoid the pressure added onto the (front or rear) surface of modules, which might cause non-uniformity or other function issue to display.