

G156XW01 V1

AU OPTRONICS CORPORATION

(V) Preliminary Specification () Final Specification

| Module | 15.6" Color TFT-LCD |
|------------|---------------------|
| Model Name | G156XW01 V1 |

| Customer | Date |
|-------------|------|
| Approved by | |
| | |

Note: This Specification is subject to change without notice.

| Approved by | Date |
|------------------------|------------------|
| <u>Debblie Chiu</u> | <u>2011/5/24</u> |
| Prepared by Wennie Lee | <u>2011/5/24</u> |
| | <u> </u> |

Desktop Display Business Group /

AU Optronics corporation

Contents

| 1.0 Handling Precautions | | 4 |
|-------------------------------------|-----|-----|
| 2.0 General Description | | 5 |
| 2.1 Display Characteristics | | 5 |
| 2.2 Optical Characteristics | | 6 |
| 3.0 Functional Block Diagram | | 10 |
| 4.0 Absolute Maximum Ratings. | | 11 |
| 4.1 TFT LCD Module | | 11 |
| 4.2 Absolute Ratings of Environment | | 11 |
| 5.0 Electrical characteristics | | 12 |
| 5.1 TFT LCD Module | | 12 |
| 5.2 Backlight Unit | | 14 |
| 6.0 Signal Characteristic | | 15 |
| 6.1 Pixel Format Image | | 15 |
| 6.2 The input data format | | 15 |
| 6.3 Signal Description | | 16 |
| 6.4 Timing Characteristics | | 18 |
| 6.5 Timing diagram | | 19 |
| 6.6 Power ON/OFF Sequence | | 20 |
| 7.0 Connector & Pin Assignment | t | 21 |
| 7.1 TET LCD Module | | 2.1 |
| 7.2 Backlight Unit | Ô,, | 22 |
| 8.0 Reliability Test | | 23 |
| 9.0 Shipping Label | | 24 |
| | | |
| 10.0 Mechanical Characteristics | | |



G156XW01 V1

AU OPTRONICS CORPORATION

Record of Revision

| Vers | ion and Date | Page | Old description | New Description | Remark |
|------|--------------|------|----------------------------|-----------------|--------|
| 0.0 | 2011/5/24 | | First Edition for Customer | N/A | |
| | | | | | |
| | | | | | |
| | | | | | |
| | | | | | |
| | | | | | |
| | | | | | |
| | | | | | |
| | | | | | |

AND Confidential For Problems Use Only 120 Albaria



G156XW01 V1

AU OPTRONICS CORPORATION

1.0 Handling Precautions

- 1) Since front polarizer is easily damaged, pay attention not to scratch it.
- 2) Be sure to turn off power supply when inserting or disconnecting from input connector.
- 3) Wipe off water drop immediately. Long contact with water may cause discoloration or spots.
- 4) When the panel surface is soiled, wipe it with absorbent cotton or other soft cloth.
- 5) Since the panel is made of glass, it may break or crack if dropped or bumped on hard surface.
- 6) Since CMOS LSI is used in this module, take care of static electricity and insure human earth when handling.
- 7) Do not open or modify the Module Assembly.
- 8) Do not press the reflector sheet at the back of the module to any directions.
- 9) In case if a Module has to be put back into the packing container slot after once it was taken out from the container, do not press the center of the LED reflector edge. Instead, press at the far ends of the LED Reflector edge softly. Otherwise the TFT Module may be damaged.
- 10) At the insertion or removal of the Signal Interface Connector, be sure not to rotate nor tilt the Interface Connector of the TFT Module.
- 11) TFT-LCD Module is not allowed to be twisted & bent even force is added on module in a very short time. Please design your display product well to avoid external force applying to module by end-user directly.
- 12) Small amount of materials without flammability grade are used in the TFT-LCD module. The TFT-LCD module should be supplied by power complied with requirements of Limited Power Source (IEC60950 or UL1950), or be applied exemption.
- 13) Severe temperature condition may result in different luminance, response time.
- 14) Continuous operating TFT-LCD Module under high temperature environment may accelerate LED light bar exhaustion and reduce luminance dramatically.
- 15) The data on this specification sheet is applicable when TFT-LCD module is placed in landscape position.
- 16) Continuous displaying fixed pattern may induce image sticking. It's recommended to use screen saver or moving content periodically if fixed pattern is displayed on the screen.



AU OPTRONICS CORPORATION

2.0 General Description

This specification applies to the 15.6 inch-wide Color a-Si TFT-LCD Module G156XW01. The display supports the HD - $1366(H) \times 768(V)$ screen format and 16.7M colors (RGB 6-bits + Hi-FRC data). All input signals are LVDS interface and this module doesn't contain an inverter board for backlight.

2.1 Display Characteristics

The following items are characteristics summary on the table under 25 □ condition:

| ITEMS | Unit | SPECIFICATIONS | | | |
|----------------------------|----------------------|--------------------------------------|--|--|--|
| Screen Diagonal | [mm] | 15.6" | | | |
| Active Area | [mm] | 344.232 (H) x 193.536 (V) | | | |
| Pixels H x V | | 1366(x3) x 768 | | | |
| Pixel Pitch | [um] | 252 (per one triad) ×252 | | | |
| Pixel Arrangement | | R.G.B. Vertical Stripe | | | |
| Display Mode | | TN Mode, Normally White | | | |
| White Luminance (Center) | [cd/m ²] | 300 cd/m ² (Typ.) | | | |
| Contrast Ratio | | 500 (Typ.) | | | |
| Optical Response Time | [msec] | 8ms (Typ., on/off) | | | |
| Nominal Input Voltage VDD | [Volt] | +5.0 V | | | |
| LCD Power Consumption | [Watt] | 2.15 W (Typ.), 2.5 W (Max.) | | | |
| LCD Fower Consumption | [vvaiij | (all black pattern) | | | |
| LED Power Consumption | [Watt] | 10.5 W (Typ.), 12 W (Max.) | | | |
| · | | (all black pattern) | | | |
| Weight | [g] | 1250 (Typ), 1350(Max.) | | | |
| Physical Size | [mm] | 363.8(W) X 215.9(H) X 16.85 (D) Typ. | | | |
| Electrical Interface | | One channel LVDS | | | |
| Support Color | | 16.7M colors (RGB 6-bit + Hi-FRC) | | | |
| Surface Treatment | - An | Anti-Glare, 3H | | | |
| RoHS Compliance | | RoHS Compliance | | | |
| Temperature Range | | | | | |
| Operating | [°CD | 0 to +50 | | | |
| Storage (Non-Operating) | [°C] | -20 to +60 | | | |
| Storage (Non-Operating) | | | | | |



AU OPTRONICS CORPORATION

2.2 Optical Characteristics


The optical characteristics are measured under stable conditions at 25 °C:

| Item | Unit | Conditions | Min. | Тур. | Max. | Note | | | |
|--|----------------------|--------------------------------------|----------|----------|--------|------|--|--|--|
| | | Horizontal (Right) CR = 10 (Left) | 75 75 | 85 85 | - | | | | |
| Viewing Angle | [degree] | Vertical (Up) CR = 10 (Down) | 70 70 | 80 80 | - | 4.0 | | | |
| Viewing Angle | [uegree] | Horizontal (Right) CR = 5 (Left) | 75 75 | 85 85 | - - | 1,2 | | | |
| | | Vertical (Up) CR = 5 (Down) | 75 75 | 85 85 | - | | | | |
| Contrast ratio | | Normal Direction | 350 | 500 | - | 3 | | | |
| | | Raising Time (T _{rR}) | _ | 6 | 9 | | | | |
| Response Time | [msec] | Falling Time (T _{rF}) | _ | 2 | 4 | 4 | | | |
| | | Raising + Falling | - | 8 | 13 | | | | |
| | | Red x | 0.591 | 0.641 | 0.691 | | | | |
| | | Red y | 0.293 | 0.343 | 0.393 | | | | |
| Color / Chromaticity | | Green x | 0.276 | 0.326 | 0.376 | | | | |
| Coordinates (CIE) | | Green y | 0.567 | 0.617 | 0.667 | 5 | | | |
| | | Blue x | 0.098 | 0.148 | 0.198 | 9 | | | |
| | | Blue y | 0.014 | 0.064 | 0.114 | | | | |
| | | White x | 0.263 | 0.313 | 0.363 | | | | |
| Color Coordinates (CIE) White | | White y | 0.279 | 0.329 | 0.379 | | | | |
| Central Luminance | [cd/m ²] | | 240 | 300 | - | 6 | | | |
| Luminance Uniformity | [%] | | 75 | 80 | - | 7 | | | |
| Crosstalk (in 60Hz) | [%] | | | | 1.5 | 8 | | | |
| Flicker | dB | | | | -20 | 9 | | | |
| Crosstalk (in 60Hz) Flicker dB -20 9 | | | | | | | | | |




Note 1: Measurement method

The LCD module should be stabilized at given temperature for 30 minutes to avoid abrupt temperature change during measuring (at surface 35 °C). In order to stabilize the luminance, the measurement should be executed after lighting Backlight for 30 minutes in a stable, windless and dark room.



Note 2: Definition of viewing angle measured by ELDIM (EZContrast 88)

Viewing angle is the measurement of contrast ratio ≥ 10 and ≥ 5 , at the screen center, over a 180° horizontal and 180° vertical range (off-normal viewing angles). The 180° viewing angle range is broken down as follows; 90° (θ) horizontal left and right and 90° (Φ) vertical, high (up) and low (down). The measurement direction is typically perpendicular to the display surface with the screen rotated about its center to develop the desired measurement viewing angle.






Note 3: Contrast ratio is measured by TOPCON SR-3

Note 4: Definition of Response time measured by Westar TRD-100A

The output signals of photo detector are measured when the input signals are changed from "Full Black" to "Full White" (rising time, Tr_R), and from "Full White" to "Full Black" (falling time, Tf_F), respectively. The response time is interval between the 10% and 90% (1 frame at 60 Hz) of amplitudes.




 $Tr_R + Tf_F = 8 \text{ msec (typ.)}.$

Note 5: Color chromaticity and coordinates (CIE) is measured by TOPCON SR-3

Note 6: Central luminance is measured by TOPCON SR-3

Note 7: Luminance uniformity of these 9 points is defined as below and measured by TOPCON SR-3



Uniformity = $\frac{\text{Minimum Luminance in 9 points (1 - 9)}}{\text{Maximum Luminance in 9 Points (1 - 9)}}$




Note 8: Crosstalk is defined as below and measured by TOPCON SR-3


 $CT = | YB - YA | / YA \times 100 (\%), Where$

YA = Luminance of measured location without gray level 0 pattern (cd/m2)


YB = Luminance of measured location with gray level 0 pattern (cd/m2)



Note 9: Test Patern: Subchecker Pattern measured by TOPCON SR-3



Method: Record dBV & DC value with TRD-100




Flicker (dB) = $20 \log \frac{AC \text{ Level(at 30 Hz)}}{C}$



3.0 Functional Block Diagram

The following diagram shows the functional block of the 15.6 inch Color TFT-LCD Module:



I/F PCB Interface:

JAE / FI-XB30SSL-HF15 STM / MSBKT2407P30HB

Mating Type:

FI-X30HL (Locked Type)

4.0 Absolute Maximum Ratings

Absolute maximum ratings of the module are as following:

4.1 TFT LCD Module

| Item | Symbol | Min | Max | Unit | Conditions |
|-------------------------|--------|-----|-----|--------|------------|
| Logic/LCD Drive Voltage | Vin | 0 | 6.0 | [Volt] | Note 1,2 |


4.2 Absolute Ratings of Environment

| ltem | Symbol | Min. | Max. | Unit | Conditions | | | | |
|-----------------------|--------|------|------|-------|------------|--|--|--|--|
| Operating Temperature | TOP | 0 | +50 | [°C] | | | | | |
| Operation Humidity | HOP | 5 | 90 | [%RH] | Note 2 | | | | |
| Storage Temperature | TST | -20 | +60 | [°C] | Note 3 | | | | |
| Storage Humidity | HST | 5 | 90 | [%RH] | | | | | |

Note 1: With in Ta (25 °C)

Note 2: Permanent damage to the device may occur if exceeding maximum values

Note 3: For quality perfermance, please refer to AUO IIS(Incoming Inspection Standard).



Operating Range

Storage Range

+



5.0 Electrical characteristics

5.1 TFT LCD Module


5.1.1 Power Specification

Input power specifications are as following:

| Symbol | Parameter | Min | Тур | Max | Unit | Conditions |
|--------|---|-----|------|-----|----------|---|
| VDD | Logic/LCD Drive Voltage | 4.5 | 5.0 | 5.5 | [Volt] | +/-10% |
| IDD | Input Current | - | 0.43 | 0.5 | [A] | VDD= 5.0V, All Black Pattern At 60Hz |
| PDD | VDD Power | ı | 2.15 | 2.5 | [Watt] | VDD= 5.0V, All Black Pattern At 60Hz |
| IRush | Inrush Current | ı | - | 2.5 | [A] | Note 1 |
| VDDrp | Allowable Logic/LCD Drive Ripple Voltage | - | - | 300 | [mV] p-p | VDD= 5.0V, All Black Pattern At 60Hz |

Note 1: Measurement conditions:

The duration of rising time of power input is 470 us.





AU OPTRONICS CORPORATION


5.1.2 Signal Electrical Characteristics

Input signals shall be low or Hi-Z state when VDD is off. Please refer to specifications of SN75LVDS82DGG (Texas Instruments) in detail.

Characteristics of each signal are as following:

| Symbol | Parameter | Min | Тур | Max | Units | Condition |
|--------|----------------------------|------|------|------|----------|-----------------------|
| VTH | Differential Input High | | +50 | .100 | [100] /] | VICM = 1.2V |
| VIII | Threshold | ı | +50 | +100 | [mV] | Note 1 |
| \/TI | Differential Input Low | -100 | 50 | | [100] /] | VICM = 1.2V |
| VTL | Threshold | -100 | -50 | _ | [mV] | Note 1 |
| VID | Input Differential Voltage | 100 | - | 600 | [mV] | Note 1 |
| VICM | Differential Input Common | .10 | .1.2 | .4.5 | D. ZI | VTH-VTL = 200MV (max) |
| VICM | Mode Voltage | +1.0 | +1.2 | +1.5 | [V] | Note 1 |

Note 1: LVDS Signal Waveform



5.2 Backlight Unit

Parameter guideline for LED Inverter is under stable conditions at 25 °C (Room Temperature):

| | 1 | | | | _ ` | |
|----------------|-----------------------|-------|------|------|-------|--------------|
| Symbol | Parameter | Min | Тур | Max | Units | Remark |
| Vcc | Input Voltage | 10.8 | 12 | 13.2 | Volt | |
| lvcc | Input Current | _ | 0.88 | - | А | 100% Dimming |
| PLED | Power Consumption | - | 10.5 | 12 | Watt | 100% Dimming |
| FPWM | PWM Dimming Frequency | 200 | - | 20k | Hz | |
| | Swing Voltage | 3 | 3.3 | 5 | | |
| | Dimming Duty Cycle | 5 | - | 100 | % | |
| I _F | LED Forward Current | - | 80 | | mA | Ta = 25°C |
| Operating Life | | 50000 | - | - | Hrs | Ta = 25°C |

Note 1: Ta means ambient temperature of TFT-LCD module.

Note 2: If G156XW01 V1 module is driven at high ambient temperature & humidity condition. The operating life will be reduced.


Note 3: Operating life means brightness goes down to 50% initial brightness. Min. operating life time is estimated data.




6.0 Signal Characteristic

6.1 Pixel Format Image

Following figure shows the relationship of the input signals and LCD pixel format.



6.2 The input data format



Note 1: R/G/B data 7:MSB, R/G/B data 0:LSB



AU OPTRONICS CORPORATION


6.3 Signal Description

The module using one LVDS receiver SN75LVDS82(Texas Instruments). LVDS is a differential signal technology for LCD interface and high speed data transfer device. LVDS transmitters shall be SN75LVDS83(negative edge sampling). The first LVDS port(RxOxxx) transmits odd pixels while the second LVDS port(RxExxx) transmits even pixels.

| PIN# | SIGNAL NAME | DESCRIPTION |
|------|-------------|--|
| 1 | Reserved | No Connection |
| 2 | Reserved | No Connection |
| 3 | Reserved | No Connection |
| 4 | GND | Ground |
| 5 | RXIN0- | -LVDS Differential Data Input, CH0 |
| 6 | RXIN0+ | +LVDS Differential Data Input, CH0 |
| 7 | GND | Ground |
| 8 | RXIN1- | -LVDS Differential Data Input, CH1 |
| 9 | RXIN1+ | +LVDS Differential Data Input, CH1 |
| 10 | GND | Ground |
| 11 | RXIN2- | -LVDS Differential Data Input, CH2 |
| 12 | RXIN2+ | +LVDS Differential Data Input, CH2 |
| 13 | GND | Ground |
| 14 | RXCLKIN- | -LVDS Differential Clock Input, CH3 |
| 15 | RXCLKIN+ | +LVDS Differential Clock Input, CH3 |
| 16 | GND | Ground |
| 17 | RXIN3- | -LVDS Differential Data Input, CH3 |
| 18 | RXIN3+ | +LVDS Differential Data Input, CH3 |
| 19 | GND | Ground |
| 20 | Reserved | Internal used (recommend no connection) |
| 21 | Reserved | Internal used (recommend no connection) |
| 22 | Reserved | Internal used (recommend no connection) |
| 23 | GND | Ground |
| 24 | GND | Ground |
| 25 | GND | Ground |
| 26 | AVDD | Power +5V, (typical) |
| 27 | AVDD | Power +5V, (typical) |
| 28 | AVDD | Power +5V, (typical) |
| 29 | AVDD | Power +5V, (typical) |
| 30 | AVDD | Power +5V, (typical) |



Note1: Start from left side





6.4 Timing Characteristics


Basically, interface timing described here is not actual input timing of LCD module but close to output timing of SN75LVDS82DGG (Texas Instruments) or equivalent.

| Item | | Symbol | Min | Тур | Max | Unit |
|-----------|---------------------------|----------|------|------|------|--------|
| Data CLK | | Tclk | 60 | 76 | 90 | [MHz] |
| H-section | Period | Th | 1446 | 1560 | 1936 | [Tclk] |
| | Display Area | Tdisp(h) | 1366 | 1366 | 1366 | [Tclk] |
| | Blanking | Tblk(h) | 80 | 200 | 570 | [Tclk] |
| | Period | Tv | 778 | 806 | 888 | [Th] |
| V-section | Display Area | Tdisp(v) | 768 | 768 | 768 | [Th] |
| | Blanking | Tblk(v) | 10 | 38 | 120 | [Th] |
| Fı | rame Rate | F | 50 | 60 | 75 | [Hz] |
| | Planking rame Rate e only | | | | | |

Note: DE mode only



6.5 Timing diagram






AU OPTRONICS CORPORATION

6.6 Power ON/OFF Sequence

VDD power and lamp on/off sequence are as follows. Interface signals are also shown in the chart. Signals from any system shall be Hi-Z state or low level when VDD is off.



| 3 | | Value | 0 | 1114 |
|-----------|------|--------------|------|-------|
| Parameter | Min. | Typ. | Max. | Units |
| T1 | 0.5 | - 0 | 10 | [ms] |
| T2 | 0 | 40 | 50 | [ms] |
| Т3 | 200 | | - | [ms] |
| T4 | 0,5 | - | 10 | [ms] |
| Т5 | 10 | - | - | [ms] |
| T6 | 10 | - | - | [ms] |
| T7 (| 0 | - | - | [ms] |
| T8 | 10 | - | - | [ms] |
| 79 | - | - | 10 | [ms] |
| T10 | 110 | - | - | [ms] |
| T11 | 0.5 | 16 | 50 | [ms] |
| T12 | - | - | 100 | [ms] |
| T13 | 1000 | - | - | [ms] |



AU OPTRONICS CORPORATION

7.0 Connector & Pin Assignment

Physical interface is described as for the connector on module. These connectors are capable of accommodating the following signals and will be following components.

7.1 TFT LCD Module

| Connector Name / Designation | Interface Connector / Interface card |
|------------------------------|--------------------------------------|
| Manufacturer | JAE STM |
| Type Part Number | FI-XB30SSL-HF15 |
| 31 | MSBKT2407P30HB |
| Mating Housing Part Number | FI-X30HL (Locked Type) |

7.1.1 Pin Assignment

| Pin# | Signal Name | Pin# | Signal Name |
|------|-------------|------|-------------|
| 1 | Reserved | 2 | Reserved |
| 3 | Reserved | 4 | GND |
| 5 | RXIN0- | 6 | RXIN0+ |
| 7 | GND | 8 | RXIM- |
| 9 | RXIN1+ | 10 | GND |
| 11 | RXIN2- | 12 | RXIN2+ |
| 13 | GND | 14 | RXCLKIN- |
| 15 | RXCLKIN+ | 16 | GND |
| 17 | RXIN3- | 18 | RXIN3+ |
| 19 | GND | 20 | Reserved |
| 21 | Reserved | 22 | Reserved |
| 23 | GND | 24 | GND |
| 25 | GND | 26 | AVDD |
| 27 | AVDD | 28 | AVDD |
| 29 | AVDD | 30 | AVDD |



AU OPTRONICS CORPORATION

7.2 Backlight Unit

Physical interface is described as for the connector on module. These connectors are capable of accommodating the following signals and will be following components.

| Connector Name / Designation | LED Connector |
|-------------------------------|------------------------------|
| Manufacturer | E&T or compatible |
| Connector Model Number | 3808K-F05N-02R or compatible |
| Mating Connector Model Number | H208K-P05N-02B or compatible |

7.2.1 LED Driver Connector Pin Assignment

| Pin# | Symbol | Signal Name |
|------|---------|--|
| 1 | Vcc | 12V |
| 2 | GND | GND |
| 3 | Enable | 5V-On / 0V-Off |
| 4 | Dimming | PWM Dimming |
| 5 | NC | NC |
| | | NC N |



8.0 Reliability Test

Environment test conditions are listed as following table.

| Items | Required Condition | Note |
|-----------------------------------|--|----------|
| Temperature Humidity Bias (THB) | Ta= 50 °C, 80%RH, 300hours | |
| High Temperature Operation (HTO) | Ta= 50 °C, 50%RH, 300hours | |
| Low Temperature Operation (LTO) | Ta= 0 °C, 300hours | |
| High Temperature Storage (HTS) | Ta= 60 °C, 300hours | |
| Low Temperature Storage (LTS) | Ta= -20 °C, 300hours | |
| Vibration Test (Non-operation) | Acceleration: 1.5 Grms Wave: Random Frequency: 10 - 200 Hz Duration: 30 Minutes each Axis (X, Y, Z) | |
| Shock Test (Non-operation) | Acceleration: 50 G Wave: Half-sine Active Time: 20 ms Direction: ±X, ±Y, ±Z (one time for each Axis) | |
| Drop Test | Height: 46 cm, package test | |
| Thermal Shock Test (TST) | -20 °C /30min, 60 °C /30min, 100 cycles | 1 |
| On/Off Test | On/10sec, Off/10sec, 30,000 cycles | |
| ESD (Electro Static Discharge) | Contact Discharge: ± 8KV, 150pF(330Ω) 1sec, 15 points, 25 times/ point. | 2 |
| ESD (Electro Static Discharge) | Air Discharge ± 15KV, 150pF(330Ω) 1sec 15 points, 25 times/ point. | Z |
| Altitude Test | Operation:10,000 ft Non-Operation:30,000 ft | |

Note 1: The TFT-LCD module will not sustain damage after being subjected to 100 cycles of rapid temperature change. A cycle of rapid temperature change consists of varying the temperature from -20 °C to 60 °C, and back again. Power is not applied during the test. After temperature cycling, the unit is placed in normal room ambient for at least 4 hours before power on.

Note 2: EN61000-4-2, ESD class B: Certain performance degradation allowed

No data lost Self-recoverable No hardware failures.

9.0 Shipping Label

The label is on the panel as shown below:



- Note 1: For Pb Free products, AUO will add 🔊 for identification.
- Note 2: For RoHS compatible products, AUO will add RoHS for identification.
- Note 3: For China RoHS compatible products, AUO will add for identification.
- AUO Internal Green Team.

 AUO Internal Green Team.

